

## **HB88RC**

### **Easy Set Instructions**

**Clear timer by puling the battery out for 30 seconds, then put them back and you will see 12:00 AM on the screen.**

### **Program**

- 1, Press program button,**
- 2, Press day button once for all 7 days, or keep pressing the day button until you get the day or days you need.**
- 3, Press the hour and min. button for your desired on time.**
- 4, Press the program Button.**
- 5, Press day button once for all 7 days, or keep pressing the day button until you get the day or days you need.**
- 6, Press the hour and min. button for you're desired off time.**
- 7, Repeat steps 1 through 6, for more on and off times.**

### **Set Clock**

- 1, Press clock button.**
- 2, Press mode button two times to auto.**
- 3, Press and hold clock button do not let go.**
- 4, Press the day button for the day it is now, still holding the clock button.**
- 5, Press the hour and min. button for the time it is right now, still holding the clock button. After you finish with time and day you can let go of the clock button. You're done.**

**To clear out a program, go to the program press and hold the mode button, then press the program button.**